

# LINEAR T8 1 or 2x40W, 36W, 32W, 25W

## Programmed Start

Programmed Start (series) Universal Voltage 120V-277V, High Frequency Electronic ballast for one or two Linear T8 40W, 36W, 32W, 25W GE, Philips, or Osram Fluorescent lamps.

### Technical Specification:

UL Listed, CUL Certified  
 EMI FCC Parts 18, Subparts C, Class A  
 Rating: Type 1 Outdoor, HL  
 Sound Rating: Class A  
 Min. Starting Temp : - 30° C  
 Max. Case Temp: 75° C  
 End of Lamp Life Protection Circuit

Surge Protection: Meets ANSI C62.41  
 Thermal Protection: CLASS P  
 Lamp Current Crest Factor: < 1.6  
 Remote Mounting Distance: 10 ft  
 Power Factor: 0.99  
 Input Frequency: 50/60HZ  
 THD: 120V < 10%  
 277V < 15%

Case Size: Series MU

Due to continuing efforts to offer improved products all specifications are subject to change without prior notice

5/3/04

NO. OF LAMPS	INPUT VOLTAGE	LAMP WATTS	INPUT WATTS	MAX INPUT CURRENT (A)	BALLAST FACTOR	MODEL
2 & 1	120V	40	84/46	0.70/0.38	0.88/0.95	SLU240T8RS
2 & 1	277V	40	84/46	0.30/0.16	0.88/0.95	"
2 & 1	120V	32	75/41	0.62/0.34	0.95/1.10	SLU240T8RS
2 & 1	277V	32	75/41	0.27/0.15	0.95/1.10	"

### 3 YEAR LIMITED WARRANTY

Manufacturer warrants to the purchaser: Electronic Ballast will be free from defects in material or workmanship from the date of manufacture conditioned upon proper storage, installation, use, and maintenance and conformance with any recommendations of Manufacturer.

### Lead Length

Colour	inch	cm
Black	18.8	48
White	18.8	48
Blue	30.9	78.5
Red	30.9	78.5
Yellow	46.4	118

Series MU L W H ML  
 Case Size: 241mm 43mm 29mm 226mm

**WARNING: Always Disconnect Power Before Handling.**  
**Case Should be Grounded. Install in Accordance with National and Local Electrical Codes.**

