

COMPACT 3x42W, 32W, 26W BIAX (TT5) 3x40W, 39W, 36W

Programmed Rapid Start

Programmed Rapid Start (series) Universal Voltage 120V-277V Electronic High Frequency ballast for three (3) Biax (TT5) 40W, 39W, 36W or Compact 42W, 32W, 26W GE, Philips or Osram Fluorescent lamps.

Technical Specification:

UL Listed, CUL Certified, ROHS compliant
EMI FCC Parts 18, Subparts C, Class A
Rating: Type 1 Outdoor
Sound Rating: Class A
Min. Starting Temp : -10° C
Max. Case Temp: 90° C

Surge Protection: Meets ANSI C62.41
Thermal Protection: CLASS P
Lamp Current Crest Factor: < 1.6
Remote Mounting Distance: 21 ft
Power Factor: 0.99
Input Frequency: 50/60HZ

For Bottom leads Specify "B" at the end of Model #

Case Size: Series FS2

Due to continuing efforts to offer improved products all specifications are subject to change without prior notice

3/01/10

NO. OF LAMPS	INPUT VOLTAGE	LAMP WATTS	AVERAGE INPUT WATTS	MAX INPUT CURRENT (A)	BALLAST FACTOR	THD %	MODEL
3	120V	40/39/36	119/102/75	0.99/0.88/0.79	1.13/0.85/0.90	<10	NAU342RS-ROHS
3	230V	40/39/36	119/102/75	0.50/0.44/0.32	1.07/0.80/0.90	<10	"
3	277V	40/39/36	119/102/75	0.43/0.38/0.35	1.07/0.81/0.90	<10/10/15	"
3	120V	42/32/26	122/85/73	1.01/0.71/0.61	0.88/0.92/0.85	<10	NAU342RS-ROHS
3	230V	42/32/26	122/85/73	0.53/0.37/0.32	0.88/0.87/0.90	<10	"
3	277V	42/32/26	122/85/73	0.44/0.31/0.29	0.88/0.87/0.90	<10	"

LIMITED WARRANTY

5 YEAR at maximum case temperature 75 deg C. 3 YEAR at maximum case temperature 90 deg C. Manufacturer warrants to the purchaser: Electronic Ballast will be free from defects in material or workmanship from the date of manufacture conditioned upon proper storage, installation, use, and maintenance and conformance with any recommendations of Manufacturer

Lead Length

Colour	inch	cm
Black	18.8	48
White	18.8	48
Blue	30.9	78.5
Red	30.9	78.5
Yellow	46.4	118



WARNING: Always Disconnect Power Before Handling.
Case Should be Grounded. Install in Accordance with National and Local Electrical Codes.

Series FS2 Case Size: L 241mm 9.5inch W 59mm 2.3inch H 37mm 1.46inch ML 226mm 8.9inch

1500 Marine Drive, #200 North Vancouver, BC V7P 1T7
TEL: 604-904-9533 FAX: 604-904-9634
EMAIL: sagelighting@shaw.ca www.sagelighting.com

*Sage
Lighting Ltd.*